

FIBARO Motion Sensor

Motion Sensor appearing as _GET_LANG

This guide covers how to fix the above listed issue that currently affects Vera Controllers.

1. Ghost appliance Modules

The Module _GET_LANG(generic_sensor,sensor) that appears with Level on it is the internal accelerometer that we need to deal with as Vera does not have a device type that can support this. The device is a child device which does not need to be visible on the devices tap, This can be solved very easily by using a simple luup code, below you will find codes required, to load these codes you need to navigate through the following menus **Apps>Develop Apps** then you will see a screen that you can enter code into

Test Luup code (Lua)

Code:*

* Required field

GO

```
luup.attr_set("invisible","1",deviceid)
```

You will need to replace 'deviceid' with your child devices Id which you can find under Settings on each the device, the code you use should look a little something like this

```
luup.attr_set("invisible","1",16)
```

After a short while the child module will disappear.

2. Motion Sensor as a Generic Device

This error is suspected to have occurred due to Fibaro changing its firmware on the device, this is quite easy to rectify by simply changing the device files to the following;

device_file: D_MotionSensor1.xml

device_json: D_MotionSensor1.json

These settings can be changed by pressing the arrow next to your device and going to advanced, you will be able to use the find function (Ctrl+F) to locate the required sections.

device_file	<input type="text" value="D_MotionSensor1.xml"/>
id	<input type="text" value="19"/>
impl_file	<input type="text"/>
time_created	<input type="text" value="1549255080"/>
category_num	<input type="text" value="11"/>
subcategory_num	<input type="text" value="0"/>
room	<input type="text" value="1"/>
poll	<input type="text" value="1549255151-0"/>
local_udn	<input type="text" value="uuid:4d494342-5342-5645-0013-000002fc"/>
device_json	<input type="text" value="D_MotionSensor1.json"/>